

P-5HD Electromechanical characteristics matrix

Stiffness coefficient matrix

$$\begin{bmatrix} C_{11}^E & C_{12}^E & C_{13}^E & 0 & 0 & 0 \\ C_{12}^E & C_{11}^E & C_{13}^E & 0 & 0 & 0 \\ C_{13}^E & C_{13}^E & C_{33}^E & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44}^E & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55}^E & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66}^E \end{bmatrix} = \begin{bmatrix} 14.6 & 10 & 9.8 & 0 & 0 & 0 \\ 10 & 14.6 & 9.8 & 0 & 0 & 0 \\ 9.8 & 9.8 & 12.1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 2.4 & 0 & 0 \\ 0 & 0 & 0 & 0 & 2.4 & 0 \\ 0 & 0 & 0 & 0 & 0 & 2.3 \end{bmatrix} \begin{matrix} \\ \\ \\ \\ \\ \\ \end{matrix} \left. \begin{matrix} \\ \\ \\ \\ \\ \\ \end{matrix} \right]^E \quad 10^{10} N/m^2$$

$$\begin{bmatrix} C_{11}^D & C_{12}^D & C_{13}^D & 0 & 0 & 0 \\ C_{12}^D & C_{11}^D & C_{13}^D & 0 & 0 & 0 \\ C_{13}^D & C_{13}^D & C_{33}^D & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44}^D & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55}^D & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66}^D \end{bmatrix} = \begin{bmatrix} 15.5 & 11 & 8.3 & 0 & 0 & 0 \\ 11 & 15.5 & 8.3 & 0 & 0 & 0 \\ 8.3 & 8.3 & 16.8 & 0 & 0 & 0 \\ 0 & 0 & 0 & 5.1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 5.1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 2.3 \end{bmatrix} \begin{matrix} \\ \\ \\ \\ \\ \\ \end{matrix} \left. \begin{matrix} \\ \\ \\ \\ \\ \\ \end{matrix} \right]^D \quad 10^{10} N/m^2$$

Elastic Flexibility Coefficient Matrix

$$\begin{bmatrix} S_{11}^E & S_{12}^E & S_{13}^E & 0 & 0 & 0 \\ S_{12}^E & S_{11}^E & S_{13}^E & 0 & 0 & 0 \\ S_{13}^E & S_{13}^E & S_{33}^E & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44}^E & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55}^E & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66}^E \end{bmatrix} = \begin{bmatrix} 16.8 & -5.1 & -9.5 & 0 & 0 & 0 \\ -5.1 & 16.8 & -9.5 & 0 & 0 & 0 \\ -9.5 & -9.5 & 23.8 & 0 & 0 & 0 \\ 0 & 0 & 0 & 42.5 & 0 & 0 \\ 0 & 0 & 0 & 0 & 42.5 & 0 \\ 0 & 0 & 0 & 0 & 0 & 43.9 \end{bmatrix} \begin{matrix} \\ \\ \\ \\ \\ \\ \end{matrix} \left. \begin{matrix} \\ \\ \\ \\ \\ \\ \end{matrix} \right]^E \quad 10^{-12} m^2/N$$

$$\begin{bmatrix} S_{11}^D & S_{12}^D & S_{13}^D & 0 & 0 & 0 \\ S_{12}^D & S_{11}^D & S_{13}^D & 0 & 0 & 0 \\ S_{13}^D & S_{13}^D & S_{33}^D & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44}^D & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55}^D & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66}^D \end{bmatrix} = \begin{bmatrix} 13.8 & -8.1 & -3.2 & 0 & 0 & 0 \\ -8.1 & 13.8 & -3.2 & 0 & 0 & 0 \\ -3.2 & -3.2 & 10.3 & 0 & 0 & 0 \\ 0 & 0 & 0 & 19.5 & 0 & 0 \\ 0 & 0 & 0 & 0 & 19.5 & 0 \\ 0 & 0 & 0 & 0 & 0 & 43.9 \end{bmatrix} \begin{matrix} \\ \\ \\ \\ \\ \\ \end{matrix} \left. \begin{matrix} \\ \\ \\ \\ \\ \\ \end{matrix} \right]^D \quad 10^{-12} m^2/N$$

Piezoelectric constant matrix

$$\begin{bmatrix} 0 & 0 & 0 & 0 & d_{15} & 0 \\ 0 & 0 & 0 & d_{24} & 0 & 0 \\ d_{31} & d_{31} & d_{33} & 0 & 0 & 0 \end{bmatrix} = \begin{bmatrix} 0 & 0 & 0 & 0 & 840 & 0 \\ 0 & 0 & 0 & 840 & 0 & 0 \\ -330 & -330 & 680 & 0 & 0 & 0 \end{bmatrix} \quad 10^{12} \text{C/N}$$

$$\begin{bmatrix} 0 & 0 & 0 & 0 & g_{15} & 0 \\ 0 & 0 & 0 & g_{24} & 0 & 0 \\ g_{31} & g_{31} & g_{33} & 0 & 0 & 0 \end{bmatrix} = \begin{bmatrix} 0 & 0 & 0 & 0 & 27.3 & 0 \\ 0 & 0 & 0 & 27.3 & 0 & 0 \\ -9.4 & -9.4 & 19.9 & 0 & 0 & 0 \end{bmatrix} \quad 10^{-3} \text{Vm/N}$$

$$\begin{bmatrix} 0 & 0 & 0 & 0 & e_{15} & 0 \\ 0 & 0 & 0 & e_{24} & 0 & 0 \\ e_{31} & e_{31} & e_{33} & 0 & 0 & 0 \end{bmatrix} = \begin{bmatrix} 0 & 0 & 0 & 0 & 19.8 & 0 \\ 0 & 0 & 0 & 19.8 & 0 & 0 \\ -12 & -12 & 19 & 0 & 0 & 0 \end{bmatrix} \quad \text{C/m}^2$$

$$\begin{bmatrix} 0 & 0 & 0 & 0 & h_{15} & 0 \\ 0 & 0 & 0 & h_{24} & 0 & 0 \\ h_{31} & h_{31} & h_{33} & 0 & 0 & 0 \end{bmatrix} = \begin{bmatrix} 0 & 0 & 0 & 0 & 14 & 0 \\ 0 & 0 & 0 & 14 & 0 & 0 \\ -8.1 & -8.1 & 12.9 & 0 & 0 & 0 \end{bmatrix} \quad 10^8 \text{V/m}$$

Clamped dielectric constant Matrix

$$\begin{bmatrix} \epsilon_{11}^S/\epsilon_0 & 0 & 0 \\ 0 & \epsilon_{11}^S/\epsilon_0 & 0 \\ 0 & 0 & \epsilon_{33}^S/\epsilon_0 \end{bmatrix} = \begin{bmatrix} 1600 & 0 & 0 \\ 0 & 1600 & 0 \\ 0 & 0 & 1660 \end{bmatrix}^S$$

Free dielectric constant matrix

$$\begin{bmatrix} \epsilon_{11}^T/\epsilon_0 & 0 & 0 \\ 0 & \epsilon_{11}^T/\epsilon_0 & 0 \\ 0 & 0 & \epsilon_{33}^T/\epsilon_0 \end{bmatrix} = \begin{bmatrix} 3490 & 0 & 0 \\ 0 & 3490 & 0 \\ 0 & 0 & 3860 \end{bmatrix}^T$$

